

Operating Instructions

Firmware SPECFIRM_xxx

spectraval 15x1

specbos 25x1

RU40/90

RU60

DE50 basic / expert

SDCM3 / SDCM4 / PE60_2 / PE65



JETI Technische Instrumente GmbH

Göschwitzer Str. 48

D-07745 Jena

Tel.: +49 3641 23292 00

Fax: +49 3641 23292 01

E-mail: sales@jeti.com

Internet: www.jeti.com

Contents

1	Overview of Commands by Application	5
2	Overview about Instrument Answers to the Firmware Commands	7
3	Commands	8
3.1	General Commands	8
3.2	PARAMeter	8
3.3	CONFigure	8
3.4	CONTRol	8
3.5	CALIBrate	8
3.6	MEASure	8
3.7	FETCH	9
3.8	CALCulate	9
3.9	MMEMory	9
3.10	STATus	9
4	Explanation of Commands	10
4.1	General Commands	10
4.2	Parameter Commands	11
4.2.1	General Settings	11
4.2.2	Settings Concerning the Detector Array and the AD Converter . .	11
4.2.3	Settings for Peripheral Components	13
4.2.3.1	Lamps/Shutter	13
4.2.3.2	Target Laser	15
4.2.3.3	LAN Interface	16
4.2.3.4	Date and Time (Real-Time-Clock)	16
4.2.3.5	Trigger	18
4.2.3.6	General-purpose input/output(GPIO)	18
4.2.4	Time Settings	19
4.2.5	Correction and Smoothing	20
4.2.6	Settings for Measurement	21
4.2.7	Permanent Storage/Backup of Parameters	23
4.3	Configuration Commands	23
4.4	Control Commands	24
4.5	Calibration Commands	25
4.6	Measuring Commands	25
4.7	Fetch Commands	26
4.8	Calculation Commands	28
4.8.1	Raw Data	28
4.8.2	Radiometric Data	29
4.9	Mass Memory Commands	31
4.10	Status Commands	31

5	Meaning of Error Codes	32
6	Meaning of Enquiry Codes	32
7	Structure of Data Stream	33
7.1	Format = 1	33
7.2	Format = 2	34
7.3	Format = 3	35
8	License Agreement	36
9	Service	38

1 Overview of Commands by Application

Direct communication with a *JETI* device/electronics can be done with special commands via the USB interface. This interface is designed as a virtual COM port, so it can be handled similarly to a serial port with the settings 8n1/ no protocol. The allowed transfer rates are 38 400 Bd, 115 200 Bd, 230 400 Bd, 921 600 Bd and 3 000 000 Bd.

The default baud rates are:

spectraval 1501/1511: 921 600 Bd

specbos 25x1: 115 200 Bd (only symbolic, real transfer rate is USB HS)

SDCM3 / DE50 basic: 3 000 000 Bd (921 600 Bd with Bluetooth module)

SDCM4 / PE60_2 / PE65 / DE50 expert: 115 200 Bd (only symbolic, real transfer rate is USB HS)

The following list shows the available command by categories. They match the SCPI standard regulations and begin with * and have the following keywords:

*PARAMeter	Get and set general parameters
*CONFigure	Get and set configuration data
*CONTRol	Control peripheral components
*CALCulate	Calculate data from the previous measurement
*CALIBrate	Get and set for calibration parameters
*MMEMory	Handling of data storage
*MEASure	Configure, start the measurement and get the data (combination of *CONF, *INIT and *FETCH)
*FETCH	Get data from previous measurement
*STATus	Information about error and enquiry status
*HELP	Output of help information

These keywords can be followed by one or two additional words, separated by colons, and by arguments. It is only necessary to use the indicated capital letters, other letters are optional.

Several commands can be extended by arguments. The meanings of the arguments are as follows:

tint	Integration time in ms, range from 0.01 ms to 65 000.0 ms
av	Average counts for measurement (1 to 10 000)

format	Output format of spectral data (for detailed description see Structure of Data Stream) 0 no output (affects all data, also calculated values) 1 L/H binary output with length 2 ASCII output, space separated (only for testing purposes). Wavelengths are interpolated with a step set by *CONF:WSTP 3 L/H binary output with length
arg	Other arguments, described in text

If commands with get and set options are used with ?, the stored value(s) will be given. If an argument is used, this argument will be set.

Note:	A space sign between command and argument is necessary (not in case of ?).
--------------	--

If a command which accepts arguments is used without arguments, then the configured arguments will be used.

If a command was successfully proceeded it will be answered by an Acknowledge sign (ACK, 06 *hex*), otherwise the error message "Not acknowledged" (NAK, 15 *hex*) will be returned. The reason of an error can be read by the command *STAT:ERR?<CR>.

Several commands can be written successively in one line, they have to be separated by semicolons.

2 Overview about Instrument Answers to the Firmware Commands

Command category	Answer
*PARA *CONF *CONTR	with setting of value and *PARA:SAVE: ACK (06 <i>hex</i>), if value is accepted NAK (15 <i>hex</i>), if value is not accepted with ? (data request): <i>data sequence</i> <CR>
*INIT	ACK (06 <i>hex</i>) immediately after command input BELL (07 <i>hex</i>) after finishing the measurement
*MEAS	ACK (06 <i>hex</i>) immediately after command input BELL (07 <i>hex</i>) after finishing the measurement <i>data sequence</i> <CR> <CR>
*FETCH *CALC	<i>data sequence</i> <CR> <CR> (in case of spectral data output) or <i>value</i> <CR> (in case of single value output)
*HELP	<i>List with commands and description</i> <CR>

3 Commands

3.1 General Commands

BOOT; HELP; IDN; RST; SLEEP; VERS;

3.2 PARAMeter

Get and set general parameters.

?; ADCR; ADCV; ALLPARA; ANCFAC; AVER; BACKUP; BAUD; BOXCA; CALIBN;
DATE; DEVNUM; DIRECT; ETH:DHCP;ETH:GWADDR; ETH:IPADDR;
ETH:MACADDR; ETH:SNMASK; FAULTPI; FAST; FIT; FLAS; FORM; FUNC; GAIN;
GPIO; LAMPE; LAMPP; LASERINT; LASERLIM; MAXTIN; MAXAVER; OFFCORR;
OFFS; OVSAMP; PDAG; PIXBIN; PIXEL; PIXRAN; PONTIM; PRESC; RESTORE;
SAVE; SDEL; SENS; SERN; SYNCFREQ; SYNCMOD; SPNUM; TEMPC; TIME; TINT;
TRIG; TRSL; WRAN;

3.3 CONFigure

Get and set configuration data

?; BATTEN; BTEN; DISPEN; ETHEN; PIEZOEN; RTCEN; SDCARDEN; MINTIN;

3.4 CONTRol

Control peripheral elements

?; GPIO; LAMP; LASER;

3.5 CALIBrate

Get and set calibration data

?; DATA; DEL; STAT;

3.6 MEASure

Start a specific measurement

?; BATT; DARK; FLIC; LIGHT; REFE; TEMPE; TIADAPT;

3.7 FETCH

Get data from previous measurement.

?; AVER:ADAPT; AVER:DARK; AVER:LAST; AVER:LIGHT; AVER:REFER; DARK;
LEVEL; LIGHT; REFE; TINT:ADAPT; TINT:DARK; TINT:LAST; TINT:LIGHT;
TINT:REFER;

3.8 CALCulate

Calculate data from the previous measurement.

?; CCT; CHROMUV; CHROMXY; CRI; DARK:WAV; DWLPE; LIGHT:WAV; PHOTO; RA-
DIO; REFER:PIX; REFER:WAV; RGB; SPRAD;

3.9 MMEMory

Access to mass memory.

?; CAT; COPY; DATA; DEL; MOVE;

3.10 STATus

Information about error and configuration status.

ENQU; ERR; TXTERR;

4 Explanation of Commands

4.1 General Commands

*BOOT<CR>	Jump to boot loader
*HELP?<CR>	help text for all commands
*RST<CR>	Software reset
*IDN?<CR>	Get device ID
	Example of answer: JETI_SDCM3 12345678
*VERS?<CR>	Get firmware version string
	Example of answer: SPECFIRM_1511 VERSION 1.3.10 070217
*SLEEP<CR>	enter power save mode

4.2 Parameter Commands

These commands allow the basic settings of the instrument. They are set in factory and normally the user has no reason to change them.

Remark: Keep in mind that changed parameters can cause errors in measurement.

4.2.1 General Settings

*PARAMeter?<CR>	Get a help list of the parameter commands
	Example of answer: *RST<CR>: softwarereset *IDN?: get device ID *VERS?: get firmware version *PARAMeter:CHANnel?: get channel count *PARAMeter:PIXel: get/set pixelcount *PARAMeter:SENSor: get/set sensor type *PARAMeter:SDElay: get/set scan delay *PARAMeter:ADCType: get/set adc parameters etc.
*PARAMeter:SPNUMber arg<CR>	Get/ Set spectrometer number arg: string with up to 15 characters (0...9, a...z)
	Example of answer for '*PARA:SPNUM?<CR>': 2005184
*PARAMeter:SERNumber arg<CR>	Get/ Set serial number of the electronics board. arg: string with up to 15 characters (0...9, a...z)
	Example of answer for '*PARA:SERN?<CR>': 15105
*PARAMeter: DEVNUMber arg<CR>	Get/ Set device serial number. arg: string with up to 15 characters (0...9, a...z)
	Example of answer for '*PARA:DEVNUM?<CR>': 1500044

4.2.2 Settings Concerning the Detector Array and the AD Converter

*PARAMeter:SENSor arg<CR>	Get/ Set imaging sensor type and pixel number arg = any valid sensor number arg = physical pixel count, max. 4096
	Example of answer for '*PARA:SENS?<CR>': 100 2048 (S11639, S13496)
*PARAMeter:PIXBINning arg<CR>	Get/ Set the pixel to bins arg = 1 ... 16
	Example of answer for '*PARA:PIXBIN?<CR>': 2
*PARAMeter:PIXEL?<CR>	Get effective pixel number (depending on pixel binning *see PIXBIN
	Example of answer for '*PARA:PIXEL?<CR>': 1024
*PARAMeter:DIRECTtion arg<CR>	Change scan direction arg = 0 (lowest pixel first) or 1 (highest pixel first)
	Example of answer for '*PARA:DIRECT?<CR>': 0
*PARAMeter:FASTscan arg<CR>	Get/ Set time to next fast cycle (in ms) arg (spectraval 15x1/SDCM3/SDCM4): 0 ms to 350 ms arg (specbos 25x1/PE60_2/PE65): 0 ms to 150 ms
	Example of answer for '*PARA:FAST?<CR>': 50 ms
*PARAMeter:PRESCan arg<CR>	Get/ Set count of fast scans before measurement scan arg = 0 ... 8
	Example of answer for '*PARA:PRESC?<CR>': 2
*PARAMeter:PDAGain arg<CR>	Get/ Set line array gain (only S8378, S9226 and G11620) arg = 0 (low) or 1 (high)
	Example of answer for '*PARA:PDAG?<CR>': 0 (low)
*PARAMeter:ADCResolution arg<CR>	Get/ Set ADC resolution (in bit) arg = 8 ... 16 [bits] Default value: 16
	Example of answer for '*PARA:ADCR?<CR>': 16

*PARAMeter:ADCVoltage arg<CR>	Get/ Set input voltage range of ADC arg = 2: 2 V, arg = 4: 4 V
	Example of answer for '*PARA:ADCV?<CR>': 2 V
*PARAMeter:OFFSet arg<CR>	Get/ Set offset value arg: –300 mV to 300 mV
	Example of answer for '*PARA:OFFS?<CR>': 150 mV
*PARAMeter:GAIN arg<CR>	Get/ Set gain value arg: 1.0 to 5.0 Default value: 1
	Example of answer for '*PARA:GAIN?<CR>': 1.0
*PARAMeter: OVSAMPling arg<CR>	Get/ Set oversampling arg: 1 to 32 Default value: 1
	Example of answer for '*PARA:GAIN?<CR>': 12
*PARAMeter:BAUD arg<CR>	Get/ Set baudrate arg = 384: 38 400 Bd arg = 115: 115 200 Bd arg = 230: 230 400 Bd arg = 921: 921 600 Bd arg = 3000: 3 000 000 Bd Default value: 921
	Example of answer '*PARA:BAUD?<CR>': 921600

4.2.3 Settings for Peripheral Components

It is possible to connect several peripheral components to the SDCM3/SDCM4/PE60_2/PE65 boards. The following commands are used to control these components.

4.2.3.1 Lamps/Shutter

Different pins of the SDCM3/SDCM4/PE60_2/PE65 boards can be used as LV-TTL lamp or shutter control output. This signal is programmable in active polarity by parameter

lamp polarity (0/1). If the parameter lamp enable is set to 1 (enabled, normal mode), it will be set active before the scan of the line array for the time determined by scan delay parameter and during the light scan or inactive during the dark scan. Additionally the signal can be controlled by control lamp command. If the parameter lamp enable is set to 2 (enabled, flash mode), the signal can control a flash light or act as a PWM signal. One can configure the interval time and the pulse length by parameter flash mode. If lamp enable is set to disabled, the signal will be left inactive and switching with control command will return an error.

In JETI devices (spectraval 15x1 / specbos 25x1) and spectrometers (RU40/90, RU60, DE50) an internal mechanical shutter is connected to this pin. Therefore the parameters should not be changed.

*PARAMeter: LAMPEnable arg<CR>	Get/ set enable state of external lamp/shutter control output arg = 0: <i>disabled</i> , arg = 1: <i>enabled (normal)</i> , arg = 2: <i>enabled (flash / PWM mode)</i> Default value: 1
	Example of answer for ‘*PARAMeter:LAMPEnable?<CR>’: 1 (enabled)
*PARAMeter: LAMPpolarity arg<CR>	Get/ set polarity of external lamp/shutter control arg = 0: <i>high</i> , arg = 1: <i>low</i> Default value: 1
	Example of answer for ‘*PARAMeter:LAMPp?<CR>’: 1 (high)
*PARAMeter:FLASHmode arg1 arg2<CR>	Get/ set interval and pulse length for external flash light arg1 (Interval in ms, SDCM3/SDCM4): 1.0...333.0 arg1 (Interval in ms, PE60_2/PE65): 1.0...133.0 arg2 (Pulse length in μ s): 2.0...10000.0 Default value: 1
	Example of answer for ‘*PARAMeter:FLASHmode?<CR>’: 100 20
*PARAMeter:SDElay arg<CR>	Get/ Set scan delay (time difference between initiating a measurement and its real start, in ms), is necessary for full shutter opening (or lamp stability). arg: 0 ms to 60 000 ms
	Example of answer for ‘*PARAMeter:SDEL?<CR>’: 35 ms

4.2.3.2 Target Laser

These parameters are only available for spectraval 15x1 and specbos 25x1.

*PARAMeter:LASERLIMit arg<CR>	Get/ Set maximum PWM duty cycle for laser diode arg = 1 ... 100% (password protected)
	Example of answer for '*PARA:LASERLIM?<CR>': 100 %
*PARAMeter: LASERINTensity arg<CR>	Get/ Set effective PWM duty cycle for laser diode arg = 1 ... 100%
	Example of answer for '*PARA:LASERINT?<CR>': 100 %

4.2.3.3 LAN Interface

*PARAMeter:ETHernet: IPADDRess arg<CR>	Get/ Set network IP address arg = 0.0.0.0 to 255.255.255.255
	Example of answer for “*PARA:ETHernet:IPADDR?<CR>”: 192.168.115.100
*PARAMeter:ETHernet: GWADDRess arg<CR>	Get/ Set network gateway address arg = 0.0.0.0 to 255.255.255.255
	Example of answer for “*PARA:ETHernet:IPADDR?<CR>”: 192.168.115.1
*PARAMeter:ETHernet: SNMASK arg<CR>	Get/ Set network subnet mask arg = 0.0.0.0 to 255.255.255.255
	Example of answer for “*PARA:ETHernet:SNMASK?<CR>”: 255.255.255.0
*PARAMeter:ETHernet: MACADDRess arg<CR>	Get/ Set network MAC address (only variable part) arg = 80:00 to 8F:FF
	Example of answer for “*PARA:ETHernet:MACADDR?<CR>”: 70:B3:D5:93:80:02
*PARAMeter:ETHernet: DHCPmode arg<CR>	Get/ Set DHCP mode arg = 0: <i>disabled,static</i> , arg = 1: <i>enabled</i>
	Example of answer for “*PARA:ETHernet:DHCP?<CR>”: 1 (DHCP enabled)

4.2.3.4 Date and Time (Real-Time-Clock)

*DATE arg<CR>	Get/ Set actual date in format YYYY-MM-DD arg = YYYY-MM-DD
	Example of answer for “*DATE?<CR>”: 2016-03-20

*TIME arg<CR>	Get/ Set the actual time in format HH:MM:SS (24h format) arg = HH:MM:SS
	Example of answer for '*TIME?<CR>': 10:10:32
*PARAMeter:PONTIME arg<CR>	Get/ Set on-time till device is switched off due to inactivity arg: 0 .. 60 minutes
	Example of answer for '*TIME?<CR>': 5

4.2.3.5 Trigger

*PARAMeter:TRIGger arg<CR>	Get/ Set trigger mode arg = 0: <i>disabled</i> arg = 1: <i>enabled, measure mode</i> ; start of a configured measurement with hardware trigger (shortcut with switch or TTL signal), last output: 07 (measurement finished, data are ready) arg = 2: <i>enabled, enquiry mode</i> ; send enquire with hardware trigger arg = 3: <i>enabled, measure and output mode</i>
	Example of answer for '*PARAMeter:TRIG?<CR>': 1 (measure mode)
*PARAMeter:TRSLope arg<CR>	Get/ Set the trigger slope arg = 0: triggering with rising edge arg = 1: triggering with falling edge Default value: 0
	Example of answer for '*PARAMeter:TRSL?<CR>': 1 (falling edge)

4.2.3.6 General-purpose input/output(GPIO)

Various hardware pins can be used as GPIO pins. Please refer to the hardware documentation to find out which GPIOs can be used.

They can be configured as digital input with either pull-up, pull-down or floating or as digital output by using '*PARAMeter:GPIO arg1 arg2 arg3' with three arguments. The first argument is the GPIO number, the second argument is direction (0 – output, 1 – input) and the third argument is the GPIO mode when configured as input (0 – floating, 1 – pull-up, 2 – pull-down). The GPIO mode will be ignored if configured as output.

The configuration can be requested by '*PARAMeter:GPIO? arg' where arg is the GPIO number.

The pins can be controlled by using '*CONTR:GPIO arg1 arg2' with two arguments. The first argument is the GPIO number and the second argument sets the pin in case of output configuration (0 – set to low, 1 – set to high). If it is configured as input the status can be requested with '*CONTR:GPIO? arg' where arg is the GPIO number.

*PARAMeter:GPIO arg1 arg2 arg3<CR>	Get/ Set GPIO configuration <i>see description above</i>
	Example of answer for '*PARAMeter:GPIO? 7<CR>': 0 1
*CONTRol:GPIO arg1 arg2<CR>	Get/ Set GPIO state <i>see description above</i>
	Example of answer for '*CONTRol:GPIO? 7<CR>': 1

4.2.4 Time Settings

*PARAMeter:TINT tint<CR>	Get/ Set default integration time (preset value: 100.0 ms) tint: 0.01 ms to 65 000.0 ms
	Example of answer for '*PARAMeter:TINT?<CR>': 100.000 ms
*PARAMeter:MAXTINT maxtint<CR>	Get/ Set maximum integration time used by adaption. Note , this parameter has nothing to do with TINT set with *PARAMeter:TINT. Its meaning is the upper border by adaption, and it is relevant <i>only</i> for adaption algorithm. With other words, it is possible that TINT (if set explicitly) > MAXTINT. maxtint: 400.0 ms to 6000.0 ms
	Example of answer for '*PARAMeter:MAXTINT?<CR>': 4000.000
*PARAMeter:MAXAVER arg<CR>	Get/ Set maximum average count for adaption arg: 1 ... 100
	Example of answer for '*PARAMeter:MAXAVER?<CR>': 2
*PARAMeter: SYNCFREQuency arg<CR>	Get/ Set source repetition rate arg: 0.100 ... 5000.00 [Hz]
	Example of answer for '*PARAMeter:SYNCFREQ?<CR>': 300.00 Hz

*PARAMeter:SYNCMODE arg<CR>	Get/ Set synchronization mode for adaption of tint arg = 0: <i>disabled</i> arg = 1: <i>enabled</i>
	Example of answer for '*PARAMeter:SYNCMOD?<CR>': 1 (enabled)

4.2.5 Correction and Smoothing

*PARAMeter:FAULTPixel arg1 arg2 ... arg20<CR>	Get/ Set faulty pixel (the order is arbitrary, successive pixel can be used, the first pixel 0 and the last pixel of the sensor cannot be used because of their missing neighbor) 0 ... real sensor pixel count – 1 arg = 0 or -1 means: faultpixel is deactivated
	Example of answer for '*PARAMeter:FAULTPI?<CR>': 38 57
*PARAMeter: OFFCORRrange start end<CR>	Get/ Set offset correction pixel range start/end: 0 ... real sensor pixel count
	Example of answer for '*PARAMeter:OFFCORR?<CR>': 100 200
*PARAMeter:ANCFACtor arg<CR>	Get/ Set the reducing factor in ANC correction (special zero line correction procedure) 0.0 ... 1.00 arg = 1.0 : no correction arg = 0.0 : negative values set to zero
	Example of answer for '*PARAMeter:ANCFAC?<CR>': 0.0
*PARAMeter:BOXCAr arg<CR>	Get/ Set boxcar mode arg: running average of pixels, odd number 1, 3, 5 ... 11. arg = 1: no boxcar integration Default value: 1
	Example of answer for '*PARAMeter:BOXCA?<CR>': 1

*PARAMeter:AVERage arg<CR>	Get/ Set default average value arg: 1 ... 10000 Default value: 1
	Example of answer for '*PARAMeter:AVER?<CR>': 1
*PARAMeter:TEMPCorr arg<CR>	Get/ Set temperature correction value arg: -5.0 ... 5.0 [K]
	Example of answer for '*PARAMeter:TEMPC?<CR>': 0.0 K

4.2.6 Settings for Measurement

*PARAMeter: CALIBNumber arg<CR>	Get/ Set calibration file number used for radiometric calculations arg = 0 ... 8 (Calibration file number) (0 = automatic selection according to attached accessory)
	Example of answer for '*PARAMeter:CALIBN?<CR>': 1
*PARAMeter:FITn fit _n <CR>	Get/ Set wavelength fit parameters $\lambda(p) = fit_0 + fit_1 \cdot p + fit_2 \cdot p^2 + fit_3 \cdot p^3 + fit_4 \cdot p^4$ p = pixel number; n = 0 to 4; fit _n : any legal float number
	Example of answer for '*PARAMeter:FIT0?<CR>': 2.729578e+02
*PARAMeter:WRANge start end step<CR>	Get/ Set wavelength range and step width for radiometric calculation and all spectra with wavelength output start = 190 ... 2699 nm end = 191 ... 2700 nm step = 1 or 5 nm
	Example of answer for '*PARAMeter:WRAN?<CR>': 400 800 5
*PARAMeter:PIXRANge start end<CR>	Get/ Set pixel range for spectra output start = 0 ... sensor pixel count-1 end = 1 ... sensor pixel count
	Example of answer for '*PARAMeter:PIXRAN?<CR>': 0 2047

*PARAMeter:FORMat format<CR>	Get/set predefined output format (see the list of arguments in format)
	Example of answer: for '*PARA:FORM?<CR>': 2
*PARAMeter:FUNCTion function<CR>	Get/ set predefined measurement function (see the list of arguments in function) Default value: 1
	Example of answer for '*PARA:FUNC?<CR>': 1
*PARAMeter: ALLPARA?<CR>	Get a list of all parameters
	Example of answer: <pre> *PARAMeter:SERNumber 1630020 *PARAMeter:SPNUmber 4215044 *PARAMeter:DEVNUmber 1510030 *PARAMeter:SENSor 100 2048 (S11639,S13496) *PARAMeter:PIXBINning 2 *PARAMeter:DIREction 1 *PARAMeter:FASTscan 0 ms *PARAMeter:PDAGain 0 (low) *PARAMeter:ADCResolution 16 *PARAMeter:ADCVoltage 4 V *PARAMeter:OFFSet -220 mV *PARAMeter:GAIN 3.0 *PARAMeter:OVSAMpling 16 *PARAMeter:BAUDrate 115200 *PARAMeter:LAMPenable 1 (enabled) *PARAMeter:LAMPpolarity 1 (high) *PARAMeter:SDElay 200 ms *PARAMeter:LASERLIMit 100 *PARAMeter:LASERINTensity 100 *PARAMeter:FIT0 1.206140e+01 *PARAMeter:FIT1 1.335971e+00 *PARAMeter:FIT2 1.476031e-03 *PARAMeter:FIT3 -2.679267e-06 *PARAMeter:FIT4 1.604261e-09 *PARAMeter:WRANge 380 780 1 *PARAMeter:TINT 20.000 ms *PARAMeter:MAXTINT 1000.000 *PARAMeter:MAXAVER 60 *PARAMeter:SYNCFREquency 100.0 Hz *PARAMeter:SYNCMODE 1 (enabled) *PARAMeter:FORMat 1 *PARAMeter:FUNCTion 3 *PARAMeter:PONTIME 0 min *PARAMeter:FAULTPIxel 0 *PARAMeter:OFFCORRrange 50 200 *PARAMeter:ANCFAC 1.00 *PARAMeter:BOXCAR 1 *PARAMeter:AVERage 1 *PARAMeter:TEMPCorr 0.00 K *PARAMeter:TRIGger 0 *PARAMeter:TRSLope 0 *PARAMeter:CALIBNumber 0 </pre>

4.2.7 Permanent Storage/Backup of Parameters

After any change of parameters this change has to be saved to make it permanent.

*PARAMeter: DEFAult<CR>	load default parameter from internal flash storage
	Example of answer: <i>ACK (06 hex)</i>
*PARAMeter:SAVE<CR>	Write parameters to internal flash storage
	Example of answer: <i>ACK (06 hex)</i>
*PARAMeter: BACKUP<CR>	backup all parameter (password protected)
	Example of answer: <i>ACK (06 hex)</i>
*PARAMeter: RESTORE<CR>	restore parameter (password protected)
	Example of answer: <i>ACK (06 hex)</i>

4.3 Configuration Commands

The configuration commands can be used to change the default status of several arguments. In contradiction to the *PARA commands the configured parameters will be stored only temporarily.

*CONFIgure?<CR>	Get a help list of the configuration commands
*CONFIgure:BTENable arg<CR>	Get/ Set bluetooth configuration arg = 0: <i>disabled</i> , arg = 1: <i>enabled</i>
	Example of answer for '*CONF:BTEN?<CR>': 1 (bluetooth enabled)
*CONFIgure:DISPENable arg<CR>	Get/ Set display configuration arg = 0: <i>disabled</i> , arg = 1: <i>enabled</i>
	Example of answer for '*CONF:DISPEN?<CR>': 1 (display enabled)

*CONFigure:ETHENable arg<CR>	Get/ Set ethernet configuration arg = 0: <i>disabled</i> , arg = 1: <i>enabled</i>
	Example of answer for '*CONF:ETHEN?<CR>': 1 (ethernet enabled)
*CONFigure: PIEZOENable arg<CR>	Get/ Set piezo shutter configuration arg = 0: <i>disabled</i> , arg = 1: <i>enabled</i>
	Example of answer for '*CONF:PIEZOEN?<CR>': 1 (piezo shutter enabled)
*CONFigure:RTCENable arg<CR>	Get/ Set rtc configuration arg = 0: <i>disabled</i> , arg = 1: <i>enabled</i>
	Example of answer for '*CONF:RTCEN?<CR>': 1 (rtc enabled)
*CONFigure: SDCARDENable arg<CR>	Get/ Set sd card configuration arg = 0: <i>disabled</i> , arg = 1: <i>enabled</i>
	Example of answer for '*CONF:SDCARDEN?<CR>': 1 (sd card enabled)
*CONFigure: MINTINT?<CR>	Get the shortest possible integration time in ms. It depends on the type of the detector array.
	Example of answer: 0.01 ms

4.4 Control Commands

These commands are used to control the peripheral elements lamp/shutter.

*CONTRol?<CR>	Get a help list of the control commands
*CONTRol:LAMP arg<CR>	Lamp on/off or open/close a shutter arg = 1 or 0
*CONTRol:LASER arg<CR>	Get/ Set the laser status arg = 0: <i>off</i> , arg = 1: <i>on</i>
	Example of answer for '*CONTR:LASER?<CR>': 1 (target laser is on)

4.5 Calibration Commands

The SPECFIRM firmware contains radiometric measurements and calculations. The basis for this radiometry is the absolute sensitivity calibration of the unit.

*CALIBrate?<CR>	Get a help list of the calibration commands
*CALIBrate:DATA arg<CR>	Write/ read calibration data to/ from internal flash (up to 8 files) arg = 0 ... 8 (Calibration file number)
	Example of answer for '*CALIB:DATA?<CR>': calibfile
*CALIBrate:DELeTe arg<CR>	Delete a calibration file arg = 0 ... 8 Calibration file number
*CALIBrate: STATus?<CR>	Returns the calibration status
	Example of answer for '*CALIB:STAT?<CR>': 1

4.6 Measuring Commands

The measuring commands contain a measurement scan and the following output of data.

*MEASure?<CR>	Get a help list of the measuring commands
*MEASure:BATTery<CR>	Run battery voltage measurement - output of voltage, percent of battery capacity and whether USB powered
	Example of answer: 4.21 100 1

*MEASure:DARKspectra tint av format<CR>	tint $\neq$ 0: Run dark measurement Data storage in dark buffer The user has to ensure that the optical input of the unit is darkened during the *MEAS:DARK measurements (is closed with an external shutter or the lamp is switched off)
	Example of answer for *MEAS:DARK 100 1 4<CR>: ACK (06 hex) BEL (07 hex) 552 551 544 549
*MEASure:LIGHTspectra tint av format<CR>	Run light measurement (exposed spectrum – opened external shutter or lamp switched on)
*MEASure:REFErrence tint av format<CR>	Run reference measurement (Difference between light measurement and dark spectrum), data storage in reference buffer data output according to selected format
*MEASure:FLICKer<CR>	Perform a flicker frequency measurement - output of flicker frequency
	Example of answer: 234.49 Hz
*MEASure:TIADAPTION arg<CR>	Perform a measurement to get the optimal integration time - output of tint and av (see Time Settings) arg = 0: <i>only adaption</i> arg = 1: <i>with additional reference measurement</i>
	Example of answer: 63.914 1
*MEASure: TEMPERature<CR>	Measure Ambient temperature
	Example of answer for "*meas:tempe<CR>": 23.77 °C

4.7 Fetch Commands

A *FETCH command can only be used if the appropriate measurement was proceeded before.

*FETCH?<CR>	Get a help list of the fetch commands
*FETCH:LIGHT format<CR>	Output of exposed spectrum values
*FETCH:DARK format<CR>	Output of dark spectrum values
*FETCH:REFERENCE format<CR>	Output of reference values
*FETCH:LEVEL<CR>	Read out of maximum counts and percentage of exposure
	Example of answer: 47186 72
*FETCH:AVER: ADAPT<CR>	Read out adapted average count (from: *meas:tiadapt)
	Example of answer: 1
*FETCH:AVER: DARK<CR>	Read out of previously used dark average count
	Example of answer: 1
*FETCH:AVER: LAST<CR>	Read out of previously used average count
	Example of answer: 1
*FETCH:AVER: LIGHT<CR>	Read out of previously used light average count
	Example of answer: 1
*FETCH:AVER: REFER<CR>	Read out of previously used reference average count
	Example of answer: 1
*FETCH:TINT: ADAPT<CR>	Read out adapted integration time (from: *meas:tiadapt)
	Example of answer: 142.040

*FETCH:TINT: DARK<CR>	Read out of previously used dark integration time
	Example of answer: 142.040
*FETCH:TINT: LAST<CR>	Read out of previously used integration time
	Example of answer: 142.040
*FETCH:TINT: LIGHT<CR>	Read out of previously used light integration time
	Example of answer: 142.040
*FETCH:TINT: REFER<CR>	Read out of previously used reference integration time
	Example of answer: 142.040

4.8 Calculation Commands

After proceeding the appropriate measurements it is possible to calculate additional values from the obtained spectrum. The *CALC:REFER and *CALC:SPRAD commands require a previous *MEAS:REFER scan or the *MEAS:DARK and *MEAS:LIGHT scans.

4.8.1 Raw Data

*CALCulate?<CR>	Get a help list of the calculation commands
*CALCulate:DARK:WAVE format<CR>	Proceed a dark spectra calculation in the defined wavelength range and step width (*PARA:WRAN).
	Example of answer: see chapter Structure of Data Stream
*CALCulate:LIGHT:WAVE format<CR>	Proceed a light spectra calculation in the defined wavelength range and step width (*PARA:WRAN).
	Example of answer: see chapter Structure of Data Stream

*CALCulate: REFERence:PIXel format<CR>	Proceed a reference spectra calculation at pixel wavelengths.
	Example of answer: see chapter Structure of Data Stream
*CALCulate: REFERence:WAVE format<CR>	Proceed a reference spectra calculation in the defined wavelength range and step width (*PARA:WRAN).
	Example of answer: see chapter Structure of Data Stream

4.8.2 Radiometric Data

*CALCulate:SPRAD arg<CR>	Proceed a calculation of the radiometric spectrum in the defined wavelength range (*PARA:WRAN) arg = 0,1,2 (output format)
	Example of answer: see chapter Structure of Data Stream
*CALCulate:CCT<CR>	Proceed the calculation of the correlated color temperature
	Example of answer: 5749.0
*CALCulate: CHROMUV<CR>	Proceed the calculation of the chromaticity u'v'
	Example of answer: 0.2056 0.4735
*CALCulate: CHROMXY<CR>	Proceed the calculation of the chromaticity xy
	Example of answer: 0.3271 0.3348

*CALCulate:CRI<CR>	Proceed the calculation of the color rendering index Ra,DC,R1 ... R15
	Example of answer: 91.26 5.2E-03 85.3 ... 84.8
*CALCulate: DWLPE<CR>	Proceed the calculation of the dominant wavelength and color purity
	Example of answer: 494.6 2.0
*CALCulate: PHOTometric<CR>	Proceed the calculation of the photometric value
	Example of answer: 9.988E+01
*CALCulate: RADIOmetric<CR>	Proceed the calculation of the radiometric value
	Example of answer: 3.299E-01
*CALCulate:RGB<CR>	Proceed the calculation of the RGB values
	Example of answer: 216.8 87.94 90.8

4.9 Mass Memory Commands

*MMEMory?<CR>	Get a help list of the memory commands
*MMEMory: CATalog?<CR>	Returns a list of all file names in user flash
	Example of answer: <pre>filename1 filename2 ... <ETX></pre>
*MMEMory:COPY src dst<CR>	Makes a duplicate of the requested src and copies its content to dst src = sourcefile dst = destinationfile
*MMEMory:DATA filename<CR>#ABC	Writes user data to internal flash (up to 15 files with max. 4KByte per file) filename = The filename can be any name up to 63 character. White-spaces are not allowed to be part of the filename! # = This character indicates the beginning of the data block. A = Number of decimal digits present in B (can be 1 - 4) B = Decimal number specifying the number of data bytes to follow in C (up to 4096 bytes are allowed) C = Actual binary user data
	Read file with *MMEMory:DATA? filename<CR>
*MMEMory:DELeTe filename<CR>	Removes a file from the device
*MMEMory:MOVE src dst<CR>	Move/rename a file

4.10 Status Commands

The status commands are used to get the information of the error and configuration conditions.

*STATus:ERRor?<CR>	Get the error code (see list of error codes)
	Example of answer: 0
*STATus: TXTError?<CR>	Get error code and description of the error
	Example of answer: 0 no error
*STATus:ENQUIry?<CR>	Get the enquiry status (see list of enquiry codes)
	Example of answer: 5 (laser target state has been changed)

5 Meaning of Error Codes

0 : no error	50 : error lamp/shutter is disabled
4 : error unknown command	120 : error overexposure
7 : error password	123 : error could not adapt integration time
10 : error argument 1	180 : error no calib file
11 : error argument 2	226 : error no memory left
12 : error argument 3	227 : error file doesn't exist
13 : error argument 4	228 : error wrong file size
15 : error missing argument	229 : error src and dst are identical
16 : error no dark measurement	230 : error no disk available
17 : error no light measurement	300 : error device was in sleep mode
18 : error no reference measurement	301 : error could not switch to sleep mode
20 : error no spectroradiometer	302 : error no RTC available
30 : error no backup available	400 : error not possible in DHCP mode

6 Meaning of Enquiry Codes

0 : no enquiry
1 : external trigger recognized
4 : accessory attached/detached
5 : laser target state has been changed
20 : external triggered dark measurement
21 : external triggered light measurement
22 : external triggered reference measurement

7 Structure of Data Stream

7.1 Format = 1

A) *MEAS:DARK / *MEAS:LIGHT / *FETCH:DARK / *FETCH:LIGHT

(L/H binary output with length)

All data transmitted as 16 bit word, low-byte first (Little Endian)

Byte	Value	Definition
0	xx yy	length
2	xx yy	first Pixel
4	xx yy	second Pixel
:	:	:
:	:	:
2+2·n	xx yy	last Pixel

n: number of pixel per line

B) *MEAS:REFER / *FETCH:REFER / *CALC:REFER:PIX

(L/H binary output with length)

All data transmitted as 32 bit integer, low-byte first (Little Endian)

Byte	Value	Definition
0	xx yy	length
2	ww xx yy zz	first Pixel
6	ww xx yy zz	second Pixel
:	:	:
:	:	:
2+4·n	ww xx yy zz	last Pixel

n: number of pixel per line

C) *CALC:SPRAD / *CALC:xxx:WAVE

(L/H binary output with length)

All data transmitted as 32 bit float, low-byte first (Little Endian)

Byte	Value	Definition
0	xx yy	length
2	ww xx yy zz	first value
6	ww xx yy zz	second value
⋮	⋮	⋮
⋮	⋮	⋮
2+4·n	ww xx yy zz	last value

*n: number of value, based on wavelength range (*para:wrn)*

7.2 Format = 2

A) Pixel and Pixel Wavelength related Measurements

(ASCII output with wavelength, separated by <CR>, closed by <ETX>)

```
250.1<TAB>5153<CR>
250.5<TAB>4118<CR>
250.9<TAB>5126<CR>
251.4<TAB>4008<CR>
...<TAB>...<CR>
<ETX>
```

B) Wavelength related Measurements (limited by *PARA:WRAN)

(ASCII output with wavelength, separated by <CR>, closed by <ETX>)

```
380<TAB>277.81<CR>
381<TAB>299.34<CR>
382<TAB>316.14<CR>
383<TAB>370.88<CR>
...<TAB>...<CR>
<ETX>
```

7.3 Format = 3

**A) *MEAS:DARK / *MEAS:LIGHT / *MEAS:REFER / *FETCH:DARK / *FETCH:LIGHT
/ *FETCH:REFER / *CALC:REFER:PIX**

(L/H binary output with length)

All data transmitted as 32 bit float, low-byte first (Little Endian)

Byte	Value	Definition
0	xx yy	length
2	ww xx yy zz	first value
6	ww xx yy zz	second value
:	:	:
:	:	:
2+4·n	ww xx yy zz	last value

n: number of pixel per line

8 License Agreement

License Agreement for JETI Technische Instrumente GmbH Software Products
IMPORTANT – READ CAREFULLY BEFORE USING THE JETI SOFTWARE

JETI hereby grants to you a non-exclusive license to use one copy of the delivered *JETI* software program (the 'software') on a single computer according to the following items:

The software is in 'use' on the computer when it is loaded into temporary memory (i.e. RAM) or installed into permanent memory (e.g. hard disk, CD-ROM, or other storage device) of the computer. However, installation on a network server for the sole purpose of distribution to one or more other computer(s) is not constitute 'use' for which a separate license is required, provided you have separate license for each computer to which the software is distributed.

It is only allowed to use the software in connection with the *JETI* product (instrument, spectrometer or OEM electronics), which was delivered with this software. For additional *JETI* products you need an extra software license.

The software is owned by *JETI* or its suppliers and is protected by German copyright laws and international treaty provisions and all other applicable national laws. Therefore, you must treat the software like any other copyrighted material (e.g. a book or musical recording) except that if the software is not copy protected you may either

- make one copy of the software solely for backup or archival purposes, or
- transfer the software to a single hard disk provided you keep the original solely for backup or archival purposes. You may not copy the user documentation provided with the software and the connected *JETI* product.

You may not:

- permit other individuals to use the software except under the terms listed above;
- modify, translate, reverse engineer, decompile, disassemble (except to the extent that this restriction is expressly prohibited by law) or create derivative works based upon the software or documentation;
- copy the software or documentation (except for back-up or archival purposes);
- rent, lease, transfer, or otherwise transfer rights to the software or documentation;
- remove any proprietary notices or labels on the software or documentation.

Any usage in a forbidden way terminates your Software license immediately.

- You agree that you are authorized only to use the software and documentation in a manner that complies with all applicable laws in the jurisdictions in which you use the software and documentation, including, but not limited to, applicable restrictions concerning copyright and other intellectual property rights.
- You may not use the software in an attempt to, or in conjunction with, any device, program or service designed to circumvent technological measures employed to control access to, or the rights in, a content file or other work protected by the copyright laws of any jurisdiction.
- If you receive the first copy of the software electronically and a second copy on physical media (e.g., CD, diskette, etc.), the second copy may be used for archival purposes only and may not be transferred to or used by any other person. This license does not grant you any right to any enhancement or update.

The software may include certain external software components ('Add-Ons'), including the Lab Windows user interface and drivers. You may only call to or otherwise use such Add-Ons through the use of the *JETI* applications. Any direct use of Add-Ons through a non-*JETI* proprietary application, including a custom or user-written application is prohibited by this Agreement.

If you have purchased *JETI* software in connection with a *JETI* product, you have the right of purchasing a software update, if it is available, for a priority price.

Title, ownership, rights, and intellectual property of the software and documentation remain in *JETI* and/or its suppliers. Title, ownership rights and intellectual property rights in and to the content accessed through the software including the content of software media demonstration files are to be retained by the applicable content owner and may be protected by applicable copyright or other law. This license gives you no rights to such content.

For the *JETI* operating environment, the following terms apply:

JETI warrants that for a period of ninety (90) days from the date of acquisition the software, if operated as directed, will substantially achieve the functionality described in the documentation. *JETI* does not warrant however that your use of the software will be uninterrupted or that the operation of the software will be error-free or secure. *JETI* also warrants that the media containing the software, if provided by *JETI*, is free from defects in material and workmanship and will so remain for ninety (90) days from the date you acquire the software.

To the maximum extend permitted by applicable law *JETI* and its suppliers disclaim all other warranties either express or implied including but not limited to implied warranties of merchantability and fitness for a particular purpose with regard to the software, the accompanying written materials and any accompanying hardware.

If the media is subjected to accident abuse or improper use during the warranty period; or if you violate the terms of this License Agreement, this warranty is immediately terminated. This warranty is void if the software is used on or in conjunction with hardware or software other than the unmodified version of hardware and software with which the software was designed to be used as described in the documentation.

This limited warranty gives you specific legal rights.

Your remedies:

JETI's sole liability for a breach of this warranty is to be in *JETI's* sole discretion:

- to replace your defective media; or
- to advise you how to achieve substantially the same functionality with the software as described in the documentation through a procedure different from that set forth in the documentation; or
- if the above remedies are impracticable, to refund the license fee, if any, you paid for the software. Repaired, corrected or replaced software and documentation covered by this limited warranty for the period remaining under the warranty that covered the original software or if longer for thirty (30) days after the date *JETI* either shipped to you the repaired or replaced software or advised you as to how to operate the software so as to achieve the functionality described in the documentation, whichever is applicable. Only if you inform *JETI* of the problem with the software during the applicable warranty period and provide evidence of the date you acquired the software will *JETI* be obligated to honor this warranty.

Under no circumstances and under no legal theory whether in tort contract or otherwise *JETI*, its suppliers or resellers are liable to you or any other person for any indirect, special, incidental or consequential damages of any character including without limitation damages for loss of goodwill, work stoppage, computer failure or malfunction or any and all other commercial damages or losses even if *JETI* have been informed of the possibility of such damages or for any claim by any other party. Further, in no event *JETI's* liability under any provision of this agreement exceeds the license fee paid to *JETI* for the software and documentation.

This software is intended for use only with properly licensed media, content, and content creation tools. It is your responsibility to ascertain whether any copyright, patent or other licenses are necessary and to obtain any such licenses to serve and/or create, compress or download such media and content. You agree to record, play back and download only those materials for which you have the necessary patent, copyright and other permissions, licenses, and/or clearances. You agree to hold harmless, indemnify and defend *JETI*, its officers, directors and employees, from and against any losses, damages, fines and expenses (including attorneys' fees and costs) arising out of or relating to any claims that you have

- viewed, downloaded, encoded, compressed, copied or transmitted any materials (other than materials provided by *JETI*) in connection with the software in violation of another party's rights or in violation of any law, or
- violated any terms of this License Agreement.

This License Agreement will automatically terminate if you fail to comply with any term hereof. No notice must be required from *JETI* to effect such termination.

Technical support for the software, as made available by *JETI*, is given directly from the *JETI* office in Jena, Germany.

This License Agreement constitutes the complete and exclusive agreement between *JETI*, its resellers and the end user, notwithstanding any variance with any purchase order or other written instrument submitted by you, whether formally rejected by *JETI* or not. The acceptance of any purchase order you place is expressly made conditional on your consent to the terms set forth herein. The terms and conditions contained in this License Agreement may not be modified except in a writing duly signed by you and an authorized representative of *JETI*. If any provision of this License Agreement is held to be unenforceable for any reason, such provision is to be reformed only to the extent necessary to make it enforceable, and such decision does not affect the enforceability of such provision under other circumstances, or of the remaining provisions hereof under all circumstances. This License Agreement is governed by the laws of Germany, without regard to conflicts of law provisions, and you hereby consent to the exclusive jurisdiction of the provincial and federal courts sitting in Germany. Any and all unresolved disputes relating in any way to, or arising out of, the software, your usage of the software or this License Agreement are to be submitted to arbitration in Germany; except that, to the extent that you have breached or have indicated your intention to breach this License Agreement in any manner which violates or may violate *JETI's* intellectual property rights, or may cause continuing or irreparable harm to *JETI* (including, but not limited to, any breach that may impact *JETI's* intellectual property rights, or a breach by reverse engineering), *JETI* may seek injunctive relief, or any other appropriate relief, in any court of competent jurisdiction.

Copyright © 2024 JETI Technische Instrumente GmbH and/or its suppliers.

JETI Technische Instrumente GmbH, Göschwitzer Str. 48, 07745 Jena, Germany. All rights reserved.

9 Service

Please contact in case of any question or technical problem:

JETI Technische Instrumente GmbH
Göschwitzer Str. 48
D-07745 Jena
GERMANY
Tel.: +49 3641 23292 00
Fax: +49 3641 23292 01
E-mail: support@jeti.com
Internet: www.jeti.com

Copyright © 2024 JETI Technische Instrumente GmbH. All rights reserved.
Software and operating instruction are delivered with respect to the License agreement and can be used only in accordance with this License agreement. The hard and software as well as the operating instruction are subject to change without notice. JETI Technische Instrumente GmbH assumes no liability or responsibility for inaccuracies and errors in the operating instruction. It is not allowed to copy this documentation or parts of it without previous written permission by JETI Technische Instrumente GmbH

July 8, 2024